

LM35

LM35 Precision Centigrade Temperature Sensors

深圳市勤思得电子有限公司 电话：0755-82711502 网址www.qsddz.com



Literature Number: SNIS159B

LM35

Precision Centigrade Temperature Sensors

General Description


The LM35 series are precision integrated-circuit temperature sensors, whose output voltage is linearly proportional to the Celsius (Centigrade) temperature. The LM35 thus has an advantage over linear temperature sensors calibrated in ° Kelvin, as the user is not required to subtract a large constant voltage from its output to obtain convenient Centigrade scaling. The LM35 does not require any external calibration or trimming to provide typical accuracies of $\pm 1/4^\circ\text{C}$ at room temperature and $\pm 3/4^\circ\text{C}$ over a full -55 to $+150^\circ\text{C}$ temperature range. Low cost is assured by trimming and calibration at the wafer level. The LM35's low output impedance, linear output, and precise inherent calibration make interfacing to readout or control circuitry especially easy. It can be used with single power supplies, or with plus and minus supplies. As it draws only $60\ \mu\text{A}$ from its supply, it has very low self-heating, less than 0.1°C in still air. The LM35 is rated to operate over a -55° to $+150^\circ\text{C}$ temperature range, while the LM35C is rated for a -40° to $+110^\circ\text{C}$ range (-10° with improved accuracy). The LM35 series is available pack-

aged in hermetic TO-46 transistor packages, while the LM35C, LM35CA, and LM35D are also available in the plastic TO-92 transistor package. The LM35D is also available in an 8-lead surface mount small outline package and a plastic TO-220 package.

Features


- Calibrated directly in ° Celsius (Centigrade)
- Linear + 10.0 mV/°C scale factor
- 0.5°C accuracy guaranteeable (at +25°C)
- Rated for full -55° to $+150^\circ\text{C}$ range
- Suitable for remote applications
- Low cost due to wafer-level trimming
- Operates from 4 to 30 volts
- Less than $60\ \mu\text{A}$ current drain
- Low self-heating, 0.08°C in still air
- Nonlinearity only $\pm 1/4^\circ\text{C}$ typical
- Low impedance output, $0.1\ \Omega$ for 1 mA load

Typical Applications



DS005516-3

FIGURE 1. Basic Centigrade Temperature Sensor (+2°C to +150°C)




DS005516-4

Choose $R_1 = -V_S/50\ \mu\text{A}$
 $V_{\text{OUT}} = +1,500\ \text{mV}$ at $+150^\circ\text{C}$
 $= +250\ \text{mV}$ at $+25^\circ\text{C}$
 $= -550\ \text{mV}$ at -55°C

FIGURE 2. Full-Range Centigrade Temperature Sensor

Connection Diagrams

TO-46
Metal Can Package*




BOTTOM VIEW
DS005516-1

*Case is connected to negative pin (GND)

Order Number LM35H, LM35AH, LM35CH, LM35CAH or LM35DH

See NS Package Number H03H


TO-92
Plastic Package



BOTTOM VIEW
DS005516-2

**Order Number LM35CZ,
LM35CAZ or LM35DZ**
See NS Package Number Z03A

SO-8
Small Outline Molded Package




DS005516-21

N.C. = No Connection

Top View
Order Number LM35DM
See NS Package Number M08A

TO-220
Plastic Package*



DS005516-24

*Tab is connected to the negative pin (GND).

Note: The LM35DT pinout is different than the discontinued LM35DP.

Order Number LM35DT
See NS Package Number TA03F

Absolute Maximum Ratings (Note 10)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

| | |
|-------------------------|-----------------|
| Supply Voltage | +35V to -0.2V |
| Output Voltage | +6V to -1.0V |
| Output Current | 10 mA |
| Storage Temp.: | |
| TO-46 Package, | -60°C to +180°C |
| TO-92 Package, | -60°C to +150°C |
| SO-8 Package, | -65°C to +150°C |
| TO-220 Package, | -65°C to +150°C |
| Lead Temp.: | |
| TO-46 Package, | |
| (Soldering, 10 seconds) | 300°C |

| | |
|---|-----------------|
| TO-92 and TO-220 Package, (Soldering, 10 seconds) | 260°C |
| SO Package (Note 12) | |
| Vapor Phase (60 seconds) | 215°C |
| Infrared (15 seconds) | 220°C |
| ESD Susceptibility (Note 11) | 2500V |
| Specified Operating Temperature Range: T_{MIN} to T_{MAX} (Note 2) | |
| LM35, LM35A | -55°C to +150°C |
| LM35C, LM35CA | -40°C to +110°C |
| LM35D | 0°C to +100°C |

Electrical Characteristics

(Notes 1, 6)

| Parameter | Conditions | LM35A | | | LM35CA | | | Units (Max.) |
|--|--|------------------------------|------------------------------|------------------------------|------------------------------|-----------------------------|------------------------------|-----------------|
| | | Typical | Tested Limit (Note 4) | Design Limit (Note 5) | Typical | Tested Limit (Note 4) | Design Limit (Note 5) | |
| Accuracy (Note 7) | $T_A = +25^\circ\text{C}$ | ± 0.2 | ± 0.5 | | ± 0.2 | ± 0.5 | | °C |
| | $T_A = -10^\circ\text{C}$ | ± 0.3 | | | ± 0.3 | | ± 1.0 | °C |
| | $T_A = T_{MAX}$ | ± 0.4 | ± 1.0 | | ± 0.4 | ± 1.0 | | °C |
| | $T_A = T_{MIN}$ | ± 0.4 | ± 1.0 | | ± 0.4 | | ± 1.5 | °C |
| Nonlinearity (Note 8) | $T_{MIN} \leq T_A \leq T_{MAX}$ | ± 0.18 | | ± 0.35 | ± 0.15 | | ± 0.3 | °C |
| Sensor Gain (Average Slope) | $T_{MIN} \leq T_A \leq T_{MAX}$ | +10.0 | +9.9, +10.1 | | +10.0 | | +9.9, +10.1 | mV/°C |
| Load Regulation (Note 3) $0 \leq I_L \leq 1$ mA | $T_A = +25^\circ\text{C}$ | ± 0.4 | ± 1.0 | | ± 0.4 | ± 1.0 | | mV/mA |
| | $T_{MIN} \leq T_A \leq T_{MAX}$ | ± 0.5 | | ± 3.0 | ± 0.5 | | ± 3.0 | mV/mA |
| Line Regulation (Note 3) | $T_A = +25^\circ\text{C}$ | ± 0.01 | ± 0.05 | | ± 0.01 | ± 0.05 | | mV/V |
| | $4V \leq V_S \leq 30V$ | ± 0.02 | | ± 0.1 | ± 0.02 | | ± 0.1 | mV/V |
| Quiescent Current (Note 9) | $V_S = +5V, +25^\circ\text{C}$ | 56 | 67 | | 56 | 67 | | μA |
| | $V_S = +5V$ | 105 | | 131 | 91 | | 114 | μA |
| | $V_S = +30V, +25^\circ\text{C}$ | 56.2 | 68 | | 56.2 | 68 | | μA |
| | $V_S = +30V$ | 105.5 | | 133 | 91.5 | | 116 | μA |
| Change of Quiescent Current (Note 3) | $4V \leq V_S \leq 30V, +25^\circ\text{C}$ | 0.2 | 1.0 | | 0.2 | 1.0 | | μA |
| | $4V \leq V_S \leq 30V$ | 0.5 | | 2.0 | 0.5 | | 2.0 | μA |
| Temperature Coefficient of Quiescent Current | | +0.39 | | +0.5 | +0.39 | | +0.5 | μA/°C |
| Minimum Temperature for Rated Accuracy | In circuit of <i>Figure 1</i> , $I_L = 0$ | +1.5 | | +2.0 | +1.5 | | +2.0 | °C |
| Long Term Stability | $T_J = T_{MAX}$, for 1000 hours | ± 0.08 | | | ± 0.08 | | | °C |

Electrical Characteristics

(Notes 1, 6)

| Parameter | Conditions | LM35 | | | LM35C, LM35D | | | Units (Max.) |
|--|---|------------------------------|------------------------------|-----------------------------|------------------------------|-----------------------------|------------------------------|------------------------------|
| | | Typical | Tested Limit (Note 4) | Design Limit (Note 5) | Typical | Tested Limit (Note 4) | Design Limit (Note 5) | |
| Accuracy, LM35, LM35C (Note 7) | $T_A = +25^\circ\text{C}$ | ± 0.4 | ± 1.0 | | ± 0.4 | ± 1.0 | | $^\circ\text{C}$ |
| | $T_A = -10^\circ\text{C}$ | ± 0.5 | | | ± 0.5 | | ± 1.5 | $^\circ\text{C}$ |
| | $T_A = T_{\text{MAX}}$ | ± 0.8 | ± 1.5 | | ± 0.8 | | ± 1.5 | $^\circ\text{C}$ |
| | $T_A = T_{\text{MIN}}$ | ± 0.8 | | ± 1.5 | ± 0.8 | | ± 2.0 | $^\circ\text{C}$ |
| Accuracy, LM35D (Note 7) | $T_A = +25^\circ\text{C}$ | | | | ± 0.6 | ± 1.5 | | $^\circ\text{C}$ |
| | $T_A = T_{\text{MAX}}$ | | | | ± 0.9 | | ± 2.0 | $^\circ\text{C}$ |
| | $T_A = T_{\text{MIN}}$ | | | | ± 0.9 | | ± 2.0 | $^\circ\text{C}$ |
| Nonlinearity (Note 8) | $T_{\text{MIN}} \leq T_A \leq T_{\text{MAX}}$ | ± 0.3 | | ± 0.5 | ± 0.2 | | ± 0.5 | $^\circ\text{C}$ |
| Sensor Gain (Average Slope) | $T_{\text{MIN}} \leq T_A \leq T_{\text{MAX}}$ | +10.0 | +9.8, +10.2 | | +10.0 | | +9.8, +10.2 | mV/ $^\circ\text{C}$ |
| Load Regulation (Note 3) $0 \leq I_L \leq 1 \text{ mA}$ | $T_A = +25^\circ\text{C}$ | ± 0.4 | ± 2.0 | | ± 0.4 | ± 2.0 | | mV/mA |
| | $T_{\text{MIN}} \leq T_A \leq T_{\text{MAX}}$ | ± 0.5 | | ± 5.0 | ± 0.5 | | ± 5.0 | mV/mA |
| Line Regulation (Note 3) | $T_A = +25^\circ\text{C}$ | ± 0.01 | ± 0.1 | | ± 0.01 | ± 0.1 | | mV/V |
| | $4\text{V} \leq V_S \leq 30\text{V}$ | ± 0.02 | | ± 0.2 | ± 0.02 | | ± 0.2 | mV/V |
| Quiescent Current (Note 9) | $V_S = +5\text{V}, +25^\circ\text{C}$ | 56 | 80 | | 56 | 80 | | μA |
| | $V_S = +5\text{V}$ | 105 | | 158 | 91 | | 138 | μA |
| | $V_S = +30\text{V}, +25^\circ\text{C}$ | 56.2 | 82 | | 56.2 | 82 | | μA |
| | $V_S = +30\text{V}$ | 105.5 | | 161 | 91.5 | | 141 | μA |
| Change of Quiescent Current (Note 3) | $4\text{V} \leq V_S \leq 30\text{V}, +25^\circ\text{C}$ | 0.2 | 2.0 | | 0.2 | 2.0 | | μA |
| | $4\text{V} \leq V_S \leq 30\text{V}$ | 0.5 | | 3.0 | 0.5 | | 3.0 | μA |
| Temperature Coefficient of Quiescent Current | | +0.39 | | +0.7 | +0.39 | | +0.7 | $\mu\text{A}/^\circ\text{C}$ |
| Minimum Temperature for Rated Accuracy | In circuit of <i>Figure 1</i> , $I_L = 0$ | +1.5 | | +2.0 | +1.5 | | +2.0 | $^\circ\text{C}$ |
| Long Term Stability | $T_J = T_{\text{MAX}}$, for 1000 hours | ± 0.08 | | | ± 0.08 | | | $^\circ\text{C}$ |

Note 1: Unless otherwise noted, these specifications apply: $-55^\circ\text{C} \leq T_J \leq +150^\circ\text{C}$ for the LM35 and LM35A; $-40^\circ\text{C} \leq T_J \leq +110^\circ\text{C}$ for the LM35C and LM35CA; and $0^\circ\text{C} \leq T_J \leq +100^\circ\text{C}$ for the LM35D. $V_S = +5\text{Vdc}$ and $I_{\text{LOAD}} = 50 \mu\text{A}$, in the circuit of *Figure 2*. These specifications also apply from $+2^\circ\text{C}$ to T_{MAX} in the circuit of *Figure 1*. Specifications in **boldface** apply over the full rated temperature range.

Note 2: Thermal resistance of the TO-46 package is $400^\circ\text{C}/\text{W}$, junction to ambient, and $24^\circ\text{C}/\text{W}$ junction to case. Thermal resistance of the TO-92 package is $180^\circ\text{C}/\text{W}$ junction to ambient. Thermal resistance of the small outline molded package is $220^\circ\text{C}/\text{W}$ junction to ambient. Thermal resistance of the TO-220 package is $90^\circ\text{C}/\text{W}$ junction to ambient. For additional thermal resistance information see table in the Applications section.

Note 3: Regulation is measured at constant junction temperature, using pulse testing with a low duty cycle. Changes in output due to heating effects can be computed by multiplying the internal dissipation by the thermal resistance.

Note 4: Tested Limits are guaranteed and 100% tested in production.

Note 5: Design Limits are guaranteed (but not 100% production tested) over the indicated temperature and supply voltage ranges. These limits are not used to calculate outgoing quality levels.

Note 6: Specifications in **boldface** apply over the full rated temperature range.

Note 7: Accuracy is defined as the error between the output voltage and $10\text{mV}/^\circ\text{C}$ times the device's case temperature, at specified conditions of voltage, current, and temperature (expressed in $^\circ\text{C}$).

Note 8: Nonlinearity is defined as the deviation of the output-voltage-versus-temperature curve from the best-fit straight line, over the device's rated temperature range.

Note 9: Quiescent current is defined in the circuit of *Figure 1*.


Note 10: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications do not apply when operating the device beyond its rated operating conditions. See Note 1.

Note 11: Human body model, 100 pF discharged through a $1.5 \text{ k}\Omega$ resistor.

Note 12: See AN-450 "Surface Mounting Methods and Their Effect on Product Reliability" or the section titled "Surface Mount" found in a current National Semiconductor Linear Data Book for other methods of soldering surface mount devices.


Typical Performance Characteristics

Thermal Resistance Junction to Air




DS005516-25

Thermal Time Constant




DS005516-26

Thermal Response in Still Air




DS005516-27

Thermal Response in Stirred Oil Bath




DS005516-28

Minimum Supply Voltage vs. Temperature




DS005516-29

Quiescent Current vs. Temperature (In Circuit of Figure 1.)




DS005516-30

Quiescent Current vs. Temperature (In Circuit of Figure 2.)




DS005516-31

Accuracy vs. Temperature (Guaranteed)



DS005516-32


Accuracy vs. Temperature (Guaranteed)




DS005516-33

Typical Performance Characteristics (Continued)

Noise Voltage



Start-Up Response



Applications

The LM35 can be applied easily in the same way as other integrated-circuit temperature sensors. It can be glued or cemented to a surface and its temperature will be within about 0.01°C of the surface temperature.

This presumes that the ambient air temperature is almost the same as the surface temperature; if the air temperature were much higher or lower than the surface temperature, the actual temperature of the LM35 die would be at an intermediate temperature between the surface temperature and the air temperature. This is especially true for the TO-92 plastic package, where the copper leads are the principal thermal path to carry heat into the device, so its temperature might be closer to the air temperature than to the surface temperature.

To minimize this problem, be sure that the wiring to the LM35, as it leaves the device, is held at the same temperature as the surface of interest. The easiest way to do this is to cover up these wires with a bead of epoxy which will insure that the leads and wires are all at the same temperature as the surface, and that the LM35 die's temperature will not be affected by the air temperature.

The TO-46 metal package can also be soldered to a metal surface or pipe without damage. Of course, in that case the V- terminal of the circuit will be grounded to that metal. Alternatively, the LM35 can be mounted inside a sealed-end metal tube, and can then be dipped into a bath or screwed into a threaded hole in a tank. As with any IC, the LM35 and accompanying wiring and circuits must be kept insulated and dry, to avoid leakage and corrosion. This is especially true if the circuit may operate at cold temperatures where condensation can occur. Printed-circuit coatings and varnishes such as Humiseal and epoxy paints or dips are often used to insure that moisture cannot corrode the LM35 or its connections.

These devices are sometimes soldered to a small light-weight heat fin, to decrease the thermal time constant and speed up the response in slowly-moving air. On the other hand, a small thermal mass may be added to the sensor, to give the steadiest reading despite small deviations in the air temperature.


Temperature Rise of LM35 Due To Self-heating (Thermal Resistance, θ_{JA})

| | TO-46, no heat sink | TO-46*, small heat fin | TO-92, no heat sink | TO-92**, small heat fin | SO-8 no heat sink | SO-8** small heat fin | TO-220 no heat sink |
|---|---------------------------|---------------------------|---------------------------|----------------------------|-------------------------|--------------------------|---------------------------|
| Still air | 400°C/W | 100°C/W | 180°C/W | 140°C/W | 220°C/W | 110°C/W | 90°C/W |
| Moving air | 100°C/W | 40°C/W | 90°C/W | 70°C/W | 105°C/W | 90°C/W | 26°C/W |
| Still oil | 100°C/W | 40°C/W | 90°C/W | 70°C/W | | | |
| Stirred oil | 50°C/W | 30°C/W | 45°C/W | 40°C/W | | | |
| (Clamped to metal, Infinite heat sink) | | (24°C/W) | | | | (55°C/W) | |

*Wakefield type 201, or 1" disc of 0.020" sheet brass, soldered to case, or similar.



**TO-92 and SO-8 packages glued and leads soldered to 1" square of 1/16" printed circuit board with 2 oz. foil or similar.

Physical Dimensions inches (millimeters) unless otherwise noted



H03H (REV C)


TO-46 Metal Can Package (H)
 Order Number LM35H, LM35AH, LM35CH,
 LM35CAH, or LM35DH
 NS Package Number H03H



M08A (REV H)

SO-8 Molded Small Outline Package (M)
 Order Number LM35DM
 NS Package Number M08A

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



DIMENSIONS ARE IN MILLIMETERS

Z03A (Rev G)

TO-92 Plastic Package (Z)
Order Number LM35CZ, LM35CAZ or LM35DZ
NS Package Number Z03A

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

 **National Semiconductor Corporation**
Americas
Tel: 1-800-272-9959
Fax: 1-800-737-7018
Email: support@nsc.com
www.national.com

National Semiconductor Europe
Fax: +49 (0) 180-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171
Français Tel: +33 (0) 1 41 91 8790

National Semiconductor Asia Pacific Customer Response Group
Tel: 65-2544466
Fax: 65-2504466
Email: ap.support@nsc.com

National Semiconductor Japan Ltd.
Tel: 81-3-5639-7560
Fax: 81-3-5639-7507

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

| | |
|------------------------|--|
| Audio | www.ti.com/audio |
| Amplifiers | amplifier.ti.com |
| Data Converters | dataconverter.ti.com |
| DLP® Products | www.dlp.com |
| DSP | dsp.ti.com |
| Clocks and Timers | www.ti.com/clocks |
| Interface | interface.ti.com |
| Logic | logic.ti.com |
| Power Mgmt | power.ti.com |
| Microcontrollers | microcontroller.ti.com |
| RFID | www.ti-rfid.com |
| OMAP Mobile Processors | www.ti.com/omap |
| Wireless Connectivity | www.ti.com/wirelessconnectivity |

Applications

| | |
|-------------------------------|--|
| Communications and Telecom | www.ti.com/communications |
| Computers and Peripherals | www.ti.com/computers |
| Consumer Electronics | www.ti.com/consumer-apps |
| Energy and Lighting | www.ti.com/energy |
| Industrial | www.ti.com/industrial |
| Medical | www.ti.com/medical |
| Security | www.ti.com/security |
| Space, Avionics and Defense | www.ti.com/space-avionics-defense |
| Transportation and Automotive | www.ti.com/automotive |
| Video and Imaging | www.ti.com/video |

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated

深圳市勤思得电子有限公司 电话：0755-82711502 网址www.qsddz.com